




Odblokowanie klawiatury w MDB

Po podłączeniu wrzutnika CC6100E w trybie MDB np. do automatu LUCE zablokowana zostaje klawiatura wrzutnika i nie ma możliwości dokonywania ustawień konfiguracyjnych.

Rozwiązanie problemu :

(podłączyć wrzutnik np. przez executive i dokonać zmiany parametru)

Zmienić parametr w adresie 125 Door na OFF

Code	LCM Display	Function Description	Accessibility
125	Accessibility options	Set LCM accessibility under door-switch status and password security	
Default		Definition	
Door-OFF PW-ON		Setup LCM accessibility under door-switch status and setup password security. Door-ON: LCM inaccessible under door closing Door-OFF: LCM accessible under door closing PW-ON: Require password to access all LCM function PW-OFF: Require no password to access all LCM function	
LCM		Descriptions	
		Press the Manual button. Use A / C to scroll to EZ code 125. Press F to enter.	
	 	Press B / E button to select setting. Press F to save the setting. The changer display saved message when setting has been overwritten successfully..	
		Manual to exit.	